Series MTX 2000 up to 50 W and up to 80 kV




A Miba Group Company

1/1

The MTX 2000 series consists of high-quality, high-precision, high-voltage dividers for high-power, use in sophisticated resistor networks. These custom designs support a wide range of resistance value, tight voltage ratios, close tolerances and low TCRs.

Features

- up to 80 kV operating voltage
- up to 50 W operating power
- Non-Inductive design
- ROHS compliant



Technical Specifications

		80
Resistance value	see model specifications below	60 -
Resistance tolerance	see model specifications below	8
Temperature coefficient	see model specifications below	Do D
Max. operating temperature	-55°C to +125°C	
Dielectric strength	> 1,000 V (25°C, 75 % relative humidity)	0 20 40 80 125 16 0
Load life	$\Delta R/R$ 0.15 % max., 1,000 hours at rated power	Ambient Temperature, °C
Moisture resistance	ΔR/R 0.25 % max.	Standard version: (no wire connection)
Thermal shock	ΔR/R 0.2 % max.	
Encapsulation	standard coating: silicone conformal we recommend 2xpolyimide coating for use in oil and potted applications (ask for details)	
Lead material	caps, nickel-plated	
Torque	1.8 Nm to 2 Nm for M4, 3.8 Nm to 4 Nm for M8	Wire connection available on special request:
Connection	standard version having no wire tap connection. Pre soldered wire connection available on special request	
Weight	depending on model no. (ask for details)	Wire (tinned copper with nickel barrier)

Dimensions in mm

Model no.	L	В	ø	D	E	F	G	I	N
2000.23	156 ± 2	14.5 ± 0.2	13.5 ± 0.5	10 ± 0.2	8.5 ± 0.2	5 ± 0.5	M4	1.0 ± 0.1	30.0 ± 1
2000.105	308 ± 2.5	31.8 ± 0.3	30.5 ± 0.5	18 ± 0.2	40 ± 2	7 ± 0.5	M8	1.0 ± 0.1	30.0 ± 1

Model Specifications

		TCR absolute 50 ppm/°C		25 ppm/°C	15 ppm/°C		
			Tolerance absolute	0.25 % - 1 %	0.1 % - 1 %	0.1 % - 1%	
Model no.	Р	V	TCR ratio	25 ppm/°C	15 ppm/°C	15 / 10 ppm /°C	
	Wattage 40°C	Voltage kV DC	Tolerance ratio	0.5 % - 0.25%	0.5 % - 0.1%	0.5 % - 0.1 %	
2000.23	10	40	R1 + R2 Ratio	2 MΩ – 2 GΩ 1:1000 – 1:20 000	20 MΩ – 1 GΩ 1:1000 – 1:20 000	20 MΩ – 500 MΩ 1:1000 – 1:10 000	
2000.105	50	80	R1 + R2 Ratio	20 MΩ – 3 GΩ 1:1000 – 1:20 000	20 MΩ – 2 GΩ 1:1000 – 1:20 000	20 MΩ – 1 GΩ 1:1000 – 1:10 000	

How to make a request

Model no._Ohmic Value_abs. & ratio Tolerance_ abs. & ratio TCR_ratio

For example:

MTX 2000.105 500M abs. tol. 2% abs. TCR 25ppm, ratio tol. 1%, ratio TCR 15ppm, 10.000:1

